



# FLEXFIRELEDs

---

LED POWER SUPPLIES

---

# COLORBRIGHT™ POWER SUPPLIES

## SINGLE COLOR STRIPS

	LENGTH	WATTS	AMPS	OUTPUT		BRAND	MODEL	
				INPUT				
				VOLTAGE				
				DC	AC			
DIMMABLE	1-6 ft	20	1.6		12 V	120 V	Zurik	ZRK-20-12VDC
	7-11 ft	40	3.3		12 V	120 V	Zurik	ZRK-40-12VDC
	12-18 ft	60	5		12 V	120 V	Zurik	ZRK-60-12VDC
	19-30 ft	100	8.3		12 V	120 V	Zurik	ZRK-100-12VDC
	31-32 ft	150	12.5		12 V	120 V	Zurik	ZRK-150-12VDC
NON DIMMABLE	1-6 ft	24	2		12 V	100-120 V	Flexfire LEDs	12V-DPS-2
	7-13 ft	48	4		12 V	100-120 V	Flexfire LEDs	12V-DPS-4
	14-21 ft	72	6		12 V	100-120 V	Flexfire LEDs	12V-DPS-6
	22-28 ft	96	8		12 V	100-120 V	Flexfire LEDs	12V-DPS-8
	29-32 ft	120	10		12 V	100-120 V	Flexfire LEDs	12V-APS-10

## COLOR CHANGING STRIPS

RGB 150	LENGTH	WATTS	AMPS	OUTPUT		BRAND	MODEL	
				INPUT				
				VOLTAGE				
				DC	AC			
NON DIMMABLE	1-9 ft	24	2		12 V	100-120 V	Flexfire LEDs	12V-DPS-2
	10-18 ft	48	4		12 V	100-120 V	Flexfire LEDs	12V-DPS-4
	19-29 ft	72	6		12 V	100-120 V	Flexfire LEDs	12V-DPS-6
	30-32 ft	96	8		12 V	100-120 V	Flexfire LEDs	12V-DPS-8

  

RGB 300	LENGTH	WATTS	AMPS	OUTPUT		BRAND	MODEL	
				INPUT				
				VOLTAGE				
				DC	AC			
NON DIMMABLE	1-5 ft	24	2		12 V	100-120 V	Flexfire LEDs	12V-DPS-2
	6-9 ft	48	4		12 V	100-120 V	Flexfire LEDs	12V-DPS-4
	10-14 ft	72	6		12 V	100-120 V	Flexfire LEDs	12V-DPS-6
	15-16 ft	96	8		12 V	100-120 V	Flexfire LEDs	12V-DPS-8

The RGB color changing strips should only be used with the non-dimming option. The magnetic drivers interfere with the RGB remote controllers which may cause feedback, flickering, or other undesired effects.

# ULTRABRIGHT™ POWER SUPPLIES

## 12V DESIGN SERIES

	LENGTH	WATTS	AMPS	OUTPUT		INPUT	VOLTAGE	BRAND	MODEL
				DC	AC				
DIMMABLE	1-4 ft	20	1.6	12 V	120 V	Zurik	ZRK-20-12VDC		
	5-8 ft	40	3.3	12 V	120 V	Zurik	ZRK-40-12VDC		
	9-12 ft	60	5	12 V	120 V	Zurik	ZRK-60-12VDC		
	13-16 ft	100	8.3	12 V	120 V	Zurik	ZRK-100-12VDC		
NON DIMMABLE	1-5 ft	24	2	12 V	100-120 V	Flexfire LEDs	12V-DPS-2		
	6-9 ft	48	4	12 V	100-120 V	Flexfire LEDs	12V-DPS-4		
	10-13 ft	72	6	12 V	100-120 V	Flexfire LEDs	12V-DPS-6		
	14-16 ft	96	8	12 V	100-120 V	Flexfire LEDs	12V-DPS-8		

## 24V ARCHITECTURAL SERIES

	LENGTH	WATTS	AMPS	OUTPUT		INPUT	VOLTAGE	BRAND	MODEL
				DC	AC				
DIMMABLE	1-3 ft	20	.83	24 V	120 V	Zurik	ZRK-20-24VDC		
	4-6 ft	40	1.66	24 V	120 V	Zurik	ZRK-40-24VDC		
	7-9 ft	50	2	24 V	120 V	Zurik	ZRK-50-24VDC		
	10-16 ft	100	4.16	24 V	120 V	Zurik	ZRK-100-24VDC		
	17-25 ft	150	6.25	24 V	120 V	Zurik	ZRK-150-24VDC		
	26-32 ft	200	8.3	24 V	120 V	Zurik	ZRK-200-24VDC		
NON DIMMABLE	1-10 ft	60	2.5	24 V	100-240 V	Flexfire LEDs	24V-DPS-2.5		
	11-16 ft	96	4	24 V	100-240 V	Flexfire LEDs	24-DPS-4		
	17-20 ft	120	5	24 V	110-240 V	Mean Well	HLG-120H-24A		
	21-32 ft	240	10	24 V	110-240 V	Mean Well	HLG-240H-24A		

## 12V INDUSTRIAL SERIES

	LENGTH	WATTS	AMPS	OUTPUT		INPUT	VOLTAGE	BRAND	MODEL
				DC	AC				
DIMMABLE	1-2 ft	20	1.6	12 V	120 V	Zurik	ZRK-20-12VDC		
	3-4 ft	40	3.3	12 V	120 V	Zurik	ZRK-40-12VDC		
	5-7 ft	60	5	12 V	120 V	Zurik	ZRK-60-12VDC		
	7-12 ft	100	8.3	12 V	120 V	Zurik	ZRK-100-12VDC		
	13-16 ft	150	12.5	12 V	120 V	Zurik	ZRK-150-12VDC		
NON DIMMABLE	1-2 ft	24	2	12 V	100-120 V	Flexfire LEDs	12V-DPS-2		
	3-5 ft	48	4	12 V	100-120 V	Flexfire LEDs	12V-DPS-4		
	6-8 ft	72	6	12 V	100-120 V	Flexfire LEDs	12V-DPS-6		
	9-11 ft	96	8	12 V	100-120 V	Flexfire LEDs	12V-DPS-8		
	12-13 ft	120	10	12 V	100-120 V	Flexfire LEDs	12V-APS-10		
	14-16 ft	150	12.5	12 V	110-240 V	Mean Well	HLG-150H-12A		